

---

One Blue Hill Plaza, 16<sup>th</sup> Floor, PO Box 1546  
Pearl River, NY 10965  
1-800-PC-AMERICA, 1-800-722-6374  
(Voice) 845-920-0800 (Fax) 845-920-0880

## Adding Custom Logos to MX800 Series Pinpads




**Note:** You must perform a firmware update before you can upload your logo to the device.

For more information please see the document titled **Firmware\_Update\_MX800\_PinPad.pdf** at:


<http://faq.pcamerica.com>

## Uploading Custom Logos and images to the PinPad


To Upload Custom Logos and/or images, open CRE/RPE and select **Manager**. Provide the requested credentials and then follow these steps.



1. Select **Setup** and then select **Setup Screen**.




2. Select the **Hardware** tab and then select **Page 1**.
3. Select **Upgrade PinPad**.



4. Select the **Image Update** tab.
5. For **Location** select **Find**.

**Note:** Before uploading your images to the PinPad make sure that the aspect ratio is 4:3. Some image resolution examples:

- 320 X 240
- 800 X 600
- 1280 X 1024




6. Locate the image/images that you would like to have displayed on the PinPad.

**Note:** If your images are not being displayed, simply type **\*.\*** in the **File name** field, this should display all files in that folder.

**Note:** Total file size of all images selected must be under 4MB.

**Note:** Animated .gif's will not animate when uploaded the frames will have to be extracted to separate files.



7. Under **Image**:

- Leave the default for the **Width** and **Height** of the images.
- For **Time Interval** set the number of seconds that the images will stay on the PinPad screen.

**Note:** If uploading an animation (series of files) then the **Time Interval** will have to be entered in as a fraction of a second (e.g. **0.1**).

- Select **Slide/Animate** to preview what will display on the PinPad.

**Note:** Optionally you can select the images separately to see how they will display.

8. Select **Perform** to begin the **Image Upload**.



9. On the screen of the PinPad you will see a message stating that the download has commenced.



10. After the download has completed you will see a message stating such. The device will then restart and return to the form agent screen.

**Note: At this time your image/images should be displayed on the screen of the PinPad.**

11. You will then receive a message on the computer confirming that it has completed.

12. Select **OK**.

**Your images should be now on the Pinpad and the device should be ready to take sales.**